


COM Express

Express-BASE6

User's Manual



Manual Revision: 2.01
Revision Date: September 11, 2013
Part Number: 50-1J035-1010



ADLINK
TECHNOLOGY INC.

Revision History

Release	Date	Change
2.00	2012/6/25	Initial release
2.01	2013/09/11	Update to B1 PCB version (COM.0 Rev.2.1, W83627DHG-PT SIO)

Table of Contents

Preface	5
1 Introduction	7
2 Special Features	8
2.1 Primary LPC based Super I/O	8
2.2 Secondary BIOS	8
2.3 Integrated Debug Port with Single Step Execution	8
2.4 Onboard Audio	8
2.5 Information LEDs	8
2.6 Power, Reset, Lid and Sleep Switches	8
3 Component Location	9
4 Function Block Diagram	10
5 Mechanical Dimensions	11
6 Connectors and Pin-outs	12
6.1 Carrier Board Signals - Type 6	12
6.2 Connector and Pinout Compatibility	12
6.3 Carrier Board Design	12
6.4 COM Express Board-to-Board Connectors	13
6.5 PCI Express Slots	15
6.6 Digital Display Interface	18
6.7 LPC Debug	19
6.8 I2C and SMB Bus (for user access)	20
6.9 USB and LAN	22
6.10 Audio	23
6.11 VGA, LVDS	24
6.12 LVDS Jumper Settings	25
6.13 Keyboard & Mouse	26
6.14 Storage: SATA	26
6.15 Serial and IrDA Ports	27
6.16 Fan Connectors	28

6.17	Power Connectors	29
6.18	Power Jumper Settings	30
6.19	Other Connectors	31
6.20	Other Jumper Settings	33
7	Secondary BIOS.....	34
7.1	SPI Secondary BIOS - COM.0 Rev. 2.0	35
8	Switches, POST, LEDs & Power	36
8.1	Mini Switches (SW1~4)	36
8.2	Module Type Display	36
8.3	POST & Indicator LEDs	37
8.4	Digital I/O LEDs	37
8.5	ATX Power Connectors	38
8.6	AT Power Mode	39
	Important Safety Instructions	40
	Getting Service	41

Preface

Copyright 2012-2013 ADLINK Technology, Inc.

This document contains proprietary information protected by copyright. All rights are reserved. No part of this manual may be reproduced by any mechanical, electronic, or other means in any form without prior written permission of the manufacturer.

Disclaimer

The information in this document is subject to change without prior notice in order to improve reliability, design, and function and does not represent a commitment on the part of the manufacturer.

In no event will the manufacturer be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use the product or documentation, even if advised of the possibility of such damages.

Environmental Responsibility

ADLINK is committed to fulfill its social responsibility to global environmental preservation through compliance with the European Union's Restriction of Hazardous Substances (RoHS) directive and Waste Electrical and Electronic Equipment (WEEE) directive. Environmental protection is a top priority for ADLINK. We have enforced measures to ensure that our products, manufacturing processes, components, and raw materials have as little impact on the environment as possible. When products are at their end of life, our customers are encouraged to dispose of them in accordance with the product disposal and/or recovery programs prescribed by their nation or company.

Trademarks

COM Express® and PICMG® are registered trademarks of the PCI Industrial Computer Manufacturers Group.

Product names mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective companies.

Conventions

Take note of the following conventions used throughout this manual to make sure that users perform certain tasks and instructions properly.



Additional information, aids, and tips that help users perform tasks.



Information to prevent *minor* physical injury, component damage, data loss, and/or program corruption when trying to complete a task.



Information to prevent *serious* physical injury, component damage, data loss, and/or program corruption when trying to complete a specific task.

1 Introduction

The COM Express approach of custom carrier combined with off the shelf system cores is an excellent solution when you need to customize but lack the time or quantity for a complete redesign. It fits most system integration projects with production volumes from 500 to 10,000 pcs per year. The COM Express concept has a great many advantages over full custom designs, it reduces engineering complexity, lowers the threshold for total project quantity and last but not least brings your product to the market in no time. The average time to design a carrier board is less than half the time of a full custom OEM board.

Express-BASE6 is a standard ATX size carrier board. Together with the COM Express Type 6 module of your choice and off the shelf add-on cards you can quickly emulate the functionality of your desired end product for software development and hardware verification.

To build a functional prototype of your target system you will need:

- ▶ COM Express Type 6 module
- ▶ Express-BASE6 carrier board
- ▶ PCI Express add on cards
- ▶ SATA storage or Flash disk solution

The Express-BASE6 is compatible with Basic and Compact form factor Type 6 pinout COM Express modules and accommodates up to three PCI Express x1 slots, one PCI Express x4 slot, one PCI Express Graphics x16 slot and one ExpressCard slot.

The Express-BASE6 is based on the PICMG COM Express (COM.0 Rev. 2.1) specification and follows the PICMG COM Express Carrier Design Guide (CDG) where possible. (see *6.3 Carrier Board Design* on page 12).

2 Special Features

2.1 Primary LPC based Super I/O

COM Express modules do not have a Super I/O chip onboard as this is considered legacy. Consequently, a Super I/O is placed on the carrier board as an optional item. The Express-BASE6 uses a Winbond W83627DHG-PT supporting COM and PS/2 Keyboard and Mouse. The Winbond W83627DHG-PT supports a -40°C to 85°C temperature range and is pin compatible with the W83627DHG-P.

2.2 Secondary BIOS

The Express-BASE6 supports the Serial Peripheral Interface (SPI) for COM.0 Rev. 2.0 modules. Selection of active BIOS can be made by jumper settings. The location of the secondary BIOS is U55 (see 3. Component Location).

2.3 Integrated Debug Port with Single Step Execution

In addition to a two-digit POST code display, the board also provides a four-digit address display. By jumper selection the board can be switched into single step BIOS execution mode. Steps are executed using a manually operated onboard mini switch.

2.4 Onboard Audio

The Express-BASE6 has a Realtek ALC886 audio codec onboard. Audio I/O is provided by a six-jack connector.


2.5 Information LEDs

General information is obtained through signaling LEDs for HDD, Power and Watchdog status. Additionally the Express-BASE6 gives information about module types being plug into the board. See *8.2 Module Type Display* on page 35 and *8.3 POST & Indicator LEDs* on page 36.


2.6 Power, Reset, Lid and Sleep Switches

The Express-BASE6 is equipped four mini switches (SW1~4) for ATX Power, Reset, and COM.0 Rev.2.0 specified "Lid" and "Sleep" functions.


3 Component Location



4 Function Block Diagram




5 Mechanical Dimensions



All ϕ tolerances $\pm 0.05\text{mm}$
 Other tolerances $\pm 0.2\text{mm}$

6 Connectors and Pin-outs

6.1 Carrier Board Signals - Type 6



6.2 Connector and Pinout Compatibility

Connectors positions and pinouts comply with pinout and signal descriptions in the “PICMG[®] COM.0 - COM Express Module Base specification, Revision 2”. This document includes: description of pinouts, signal descriptions and mechanical characteristics of the COM Express specification. The Express-BASE6 is compatible with COM Express modules in **Basic and Compact form factor, Type 6 pinout, COM.0 Rev. 2.1**.

6.3 Carrier Board Design


The Express-BASE6 follows the PICMG COM Express Carrier Design Guide (CDG) where possible. However, the CDG was written for COM Express Type 2 modules and currently does not cover areas such as USB 3.0 or the newly introduced DDI channels on the new pinout of the Type 6 CD connector. So while the CDG is still a valuable design tool, be forewarned where signals specific to Type 6 modules are concerned. The Express-BASE6 design and schematics are fully verified, and we recommend that you follow them as a reference for your carrier board design.

Express-BASE6 Schematics and Mechanical files as well as the CDG for Type 2 modules can be downloaded from the ADLINK Express-BASE6 product webpage:

http://www.adlinktech.com/PD/web/PD_detail.php?cKind=&pid=1074

6.4 COM Express Board-to-Board Connectors

Signals and Pinout for:
COM Express Type 6.



Row A		Row B	
Pin No.	Pin Name	Pin No.	Pin Name
A1	GND(FIXED)	B1	GND(FIXED)
A2	GBE0_MDI3-	B2	GBE0_ACT#
A3	GBE0_MDI3+	B3	LPC_FRAME#
A4	GBE0_LINK100#	B4	LPC_AD0
A5	GBE0_LINK1000#	B5	LPC_AD1
A6	GBE0_MDI2-	B6	LPC_AD2
A7	GBE0_MDI2+	B7	LPC_AD3
A8	GBE0_LINK#	B8	LPC_DRQ0#
A9	GBE0_MDI1-	B9	LPC_DRQ1#
A10	GBE0_MDI1+	B10	LPC_CLK
A11	GND(FIXED)	B11	GND(FIXED)
A12	GBE0_MDI0-	B12	PWRBTN#
A13	GBE0_MDI0+	B13	SMB_CLK
A14	GBE0_CTREF	B14	SMB_DAT
A15	SUS_S3#	B15	SMB_ALERT#
A16	SATA0_TX+	B16	SATA1_TX+
A17	SATA0_TX-	B17	SATA1_TX-
A18	SUS_S4#	B18	SUS_STAT#
A19	SATA0_RX+	B19	SATA1_RX+
A20	SATA0_RX-	B20	SATA1_RX-
A21	GND(FIXED)	B21	GND(FIXED)
A22	SATA2_TX+	B22	SATA3_TX+
A23	SATA2_TX-	B23	SATA3_TX-
A24	SUS_S5#	B24	PWR_OK
A25	SATA2_RX+	B25	SATA3_RX+
A26	SATA2_RX-	B26	SATA3_RX-
A27	BATLOW#	B27	WDT
A28	(S)ATA_ACT#	B28	AC/HDA_SDIN2
A29	AC/HDA_SYNC	B29	AC/HDA_SDIN1
A30	AC/HDA_RST#	B30	AC/HDA_SDIN0
A31	GND(FIXED)	B31	GND(FIXED)
A32	AC/HDA_BITCLK	B32	SPKR
A33	AC/HDA_SDOUT	B33	I2C_CLK
A34	BIOS_DIS0#	B34	I2C_DAT
A35	THRMTRIP#	B35	THRM#
A36	US B6-	B36	US B7-
A37	US B6+	B37	US B7+
A38	US B_6_7_OC#	B38	US B_4_5_OC#
A39	US B4-	B39	US B5-
A40	US B4+	B40	US B5+
A41	GND(FIXED)	B41	GND(FIXED)
A42	US B2-	B42	US B3-
A43	US B2+	B43	US B3+
A44	US B_2_3_OC#	B44	US B_0_1_OC#
A45	US B0-	B45	US B1-
A46	US B0+	B46	US B1+
A47	VCC_RTC	B47	EXCD1_PERST#
A48	EXCD0_PERST#	B48	EXCD1_CPPE#
A49	EXCD0_CPPE#	B49	SYS_RESET#
A50	LPC_SERIRO	B50	CB_RESET#

Row C		Row D	
Pin No.	Pin Name	Pin No.	Pin Name
C1	GND(FIXED)	D1	GND(FIXED)
C2	GND	D2	GND
C3	USB_SSRX0-	D3	USB_SSTX0-
C4	USB_SSRX0+	D4	USB_SSTX0+
C5	GND	D5	GND
C6	USB_SSRX1-	D6	USB_SSTX1-
C7	USB_SSRX1+	D7	USB_SSTX1+
C8	GND	D8	GND
C9	USB_SSRX2-	D9	USB_SSTX2-
C10	USB_SSRX2+	D10	USB_SSTX2+
C11	GND(FIXED)	D11	GND(FIXED)
C12	USB_SSRX3-	D12	USB_SSTX3-
C13	USB_SSRX3+	D13	USB_SSTX3+
C14	GND	D14	GND
C15	DDI1_PAIR6+	D15	DDI1_CTRLCLK_AUX+
C16	DDI1_PAIR6-	D16	DDI1_CTRLDATA_AUX-
C17	RSVD	D17	RSVD
C18	RSVD	D18	RSVD
C19	PCIE_RX6+	D19	PCIE_TX6+
C20	PCIE_RX6-	D20	PCIE_TX6-
C21	GND(FIXED)	D21	GND(FIXED)
C22	PCIE_RX7+	D22	PCIE_TX7+
C23	PCIE_RX7-	D23	PCIE_TX7-
C24	DDI1_HPD	D24	RSVD
C25	DDI1_PAIR4+	D25	RSVD
C26	DDI1_PAIR4-	D26	DDI1_PAIR0+
C27	RSVD	D27	DDI1_PAIR0-
C28	RSVD	D28	RSVD
C29	DDI1_PAIR5+	D29	DDI1_PAIR1+
C30	DDI1_PAIR5-	D30	DDI1_PAIR1-
C31	GND(FIXED)	D31	GND(FIXED)
C32	DDI2_CTRLCLK_AUX+	D32	DDI1_PAIR2+
C33	DDI2_CTRLDATA_AUX-	D33	DDI1_PAIR2-
C34	DDI2_DDC_AUX_SEL	D34	DDI1_DDC_AUX_SEL
C35	RSVD	D35	RSVD
C36	DDI3_CTRLCLK_AUX+	D36	DDI1_PAIR3+
C37	DDI3_CTRLDATA_AUX-	D37	DDI1_PAIR3-
C38	DDI3_DDC_AUX_SEL	D38	RSVD
C39	DDI3_PAIR0+	D39	DDI2_PAIR0+
C40	DDI3_PAIR0-	D40	DDI2_PAIR0-
C41	GND(FIXED)	D41	GND(FIXED)
C42	DDI3_PAIR1+	D42	DDI2_PAIR1+
C43	DDI3_PAIR1-	D43	DDI2_PAIR1-
C44	DDI3_HPD	D44	DDI2_HPD
C45	RSVD	D45	RSVD
C46	DDI3_PAIR2+	D46	DDI2_PAIR2+
C47	DDI3_PAIR2-	D47	DDI2_PAIR2-
C48	RSVD	D48	RSVD
C49	DDI3_PAIR3+	D49	DDI2_PAIR3+
C50	DDI3_PAIR3-	D50	DDI2_PAIR3-


COM Express Board-to-Board Connectors (cont'd):

Row A		Row B		Row C		Row D	
A51	GND(FIXED)	B51	GND(FIXED)	C51	GND(FIXED)	D51	GND(FIXED)
A52	PCIE TX5+	B52	PCIE RX5+	C52	PEG RX0+	D52	PEG TX0+
A53	PCIE TX5-	B53	PCIE RX5-	C53	PEG RX0-	D53	PEG TX0-
A54	GPI0	B54	GPO1	C54	TYPE0#	D54	PEG LANE RV#
A55	PCIE TX4+	B55	PCIE RX4+	C55	PEG RX1+	D55	PEG TX1+
A56	PCIE TX4-	B56	PCIE RX4-	C56	PEG RX1-	D56	PEG TX1-
A57	GND	B57	GPO2	C57	TYPE1#	D57	TYPE2#
A58	PCIE TX3+	B58	PCIE RX3+	C58	PEG RX2+	D58	PEG TX2+
A59	PCIE TX3-	B59	PCIE RX3-	C59	PEG RX2-	D59	PEG TX2-
A60	GND(FIXED)	B60	GND(FIXED)	C60	GND(FIXED)	D60	GND(FIXED)
A61	PCIE TX2+	B61	PCIE RX2+	C61	PEG RX3+	D61	PEG TX3+
A62	PCIE TX2-	B62	PCIE RX2-	C62	PEG RX3-	D62	PEG TX3-
A63	GPI1	B63	GPO3	C63	RSVD	D63	RSVD
A64	PCIE TX1+	B64	PCIE RX1+	C64	RSVD	D64	RSVD
A65	PCIE TX1-	B65	PCIE RX1-	C65	PEG RX4+	D65	PEG TX4+
A66	GND	B66	WAKE0#	C66	PEG RX4-	D66	PEG TX4-
A67	GPI2	B67	WAKE1#	C67	RSVD	D67	GND
A68	PCIE TX0+	B68	PCIE RX0+	C68	PEG RX5+	D68	PEG TX5+
A69	PCIE TX0-	B69	PCIE RX0-	C69	PEG RX5-	D69	PEG TX5-
A70	GND(FIXED)	B70	GND(FIXED)	C70	GND(FIXED)	D70	GND(FIXED)
A71	LVDS_A0+	B71	LVDS_B0+	C71	PEG RX6+	D71	PEG TX6+
A72	LVDS_A0-	B72	LVDS_B0-	C72	PEG RX6-	D72	PEG TX6-
A73	LVDS_A1+	B73	LVDS_B1+	C73	GND	D73	GND
A74	LVDS_A1-	B74	LVDS_B1-	C74	PEG RX7+	D74	PEG TX7+
A75	LVDS_A2+	B75	LVDS_B2+	C75	PEG RX7-	D75	PEG TX7-
A76	LVDS_A2-	B76	LVDS_B2-	C76	GND	D76	GND
A77	LVDS_VDD_EN	B77	LVDS_B3+	C77	RSVD	D77	RSVD
A78	LVDS_A3+	B78	LVDS_B3-	C78	PEG RX8+	D78	PEG TX8+
A79	LVDS_A3-	B79	LVDS_BKLT_EN	C79	PEG RX8-	D79	PEG TX8-
A80	GND(FIXED)	B80	GND(FIXED)	C80	GND(FIXED)	D80	GND(FIXED)
A81	LVDS_A_CK+	B81	LVDS_B_CK+	C81	PEG RX9+	D81	PEG TX9+
A82	LVDS_A_CK-	B82	LVDS_B_CK-	C82	PEG RX9-	D82	PEG TX9-
A83	LVDS_I2C_CK	B83	LVDS_BKLT_CTRL	C83	TPM_PP	D83	RSVD
A84	LVDS_I2C_DAT	B84	VCC 5V_SBY	C84	GND	D84	GND
A85	GPI3	B85	VCC 5V_SBY	C85	PEG RX10+	D85	PEG TX10+
A86	RSVD	B86	VCC 5V_SBY	C86	PEG RX10-	D86	PEG TX10-
A87	RSVD	B87	VCC 5V_SBY	C87	GND	D87	GND
A88	PCIE_CLK_REF+	B88	BIOS_DIS1#	C88	PEG RX11+	D88	PEG TX11+
A89	PCIE_CLK_REF-	B89	VGA_RED	C89	PEG RX11-	D89	PEG TX11-
A90	GND(FIXED)	B90	GND(FIXED)	C90	GND(FIXED)	D90	GND(FIXED)
A91	SPI_POWER	B91	VGA_GRN	C91	PEG RX12+	D91	PEG TX12+
A92	SPI_MISO	B92	VGA_BLU	C92	PEG RX12-	D92	PEG TX12-
A93	GPO0	B93	VGA_HSYNC	C93	GND	D93	GND
A94	SPI_CLK	B94	VGA_VSYNC	C94	PEG RX13+	D94	PEG TX13+
A95	SPI_MOSI	B95	VGA_I2C_CK	C95	PEG RX13-	D95	PEG TX13-
A96	TPM_PP	B96	VGA_I2C_DAT	C96	GND	D96	GND
A97	TYPE10#	B97	SPI_CS#	C97	RSVD	D97	RSVD
A98	SER0_TX	B98	RSVD	C98	PEG RX14+	D98	PEG TX14+
A99	SER0_RX	B99	RSVD	C99	PEG RX14-	D99	PEG TX14-
A100	GND(FIXED)	B100	GND(FIXED)	C100	GND(FIXED)	D100	GND(FIXED)
A101	SER1_TX	B101	FAN_PWMOUT	C101	PEG RX15+	D101	PEG TX15+
A102	SER1_RX	B102	FAN_TACHIN	C102	PEG RX15-	D102	PEG TX15-
A103	LID#	B103	SLEEP#	C103	GND	D103	GND
A104	VCC 12V	B104	VCC 12V	C104	VCC 12V	D104	VCC 12V
A105	VCC 12V	B105	VCC 12V	C105	VCC 12V	D105	VCC 12V
A106	VCC 12V	B106	VCC 12V	C106	VCC 12V	D106	VCC 12V
A107	VCC 12V	B107	VCC 12V	C107	VCC 12V	D107	VCC 12V
A108	VCC 12V	B108	VCC 12V	C108	VCC 12V	D108	VCC 12V
A109	VCC 12V	B109	VCC 12V	C109	VCC 12V	D109	VCC 12V
A110	GND(FIXED)	B110	GND(FIXED)	C110	GND(FIXED)	D110	GND(FIXED)

6.5 PCI Express Slots

PCI Express x1:

PCIE4
PCIE5
PCIE7
(from corresponding PCIE n
signals on AB connector)



Pin	Signal	Pin	Signal
B1	+ 12V	A1	NC
B2	+ 12V	A2	+ 12V
B3	NC	A3	+ 12V
B4	GND	A4	GND
B5	SMB_CK	A5	TCK
B6	SMB_DAT	A6	TDI
B7	GND	A7	NC
B8	+ 3.3V	A8	TMS
B9	TRST#	A9	+ 3.3V
B10	+3.3VSB	A10	+ 3.3V
B11	WAKE#	A11	PERST#
B12	NC	A12	GND
B13	GND	A13	REFCLK+
B14	PETp0	A14	REFCLK-
B15	PETn0	A15	GND
B16	GND	A16	PERp0
B17	NC	A17	PERn0
B18	GND	A18	GND

PCIE6:


ExpressCard - PCIe only
(from PCIE6 signal on AB connector)



Pin	Signal	Pin	Signal
1	GND	14	+3.3V
2	TP23	15	+3.3V
3	TP24	16	CLKREQ#
4	CPUSB#	17	CPPE#
5	RESERVED	18	REFCLK-
6	RESERVED	19	REFCLK+
7	SMB_CK	20	GND
8	SMB_DAT	21	PERn0
9	+1.5V	22	PERp0
10	+1.5V	23	GND
11	WAKE#	24	PETn0
12	+3.3VSB	25	PETp0
13	PERST#	26	GND

PCIE x4

(from PCIE0~3 signals
on AB connector)



Pin	Signal	Pin	Signal
B1	+ 12V	A1	NC
B2	+ 12V	A2	+ 12V
B3	NC	A3	+ 12V
B4	GND	A4	GND
B5	SMB_CK	A5	TCK
B6	SMB_DAT	A6	TDI
B7	GND	A7	NC
B8	+ 3.3V	A8	TMS
B9	TRST#	A9	+ 3.3V
B10	+3.3VSB	A10	+ 3.3V
B11	WAKE#	A11	PERST#
B12	NC	A12	GND
B13	GND	A13	REFCLK+
B14	PETp0	A14	REFCLK-
B15	PETn0	A15	GND
B16	GND	A16	PERp0
B17	RSVD	A17	PERn0
B18	GND	A18	GND
B19	PETp1	A19	NC
B20	PETn1	A20	GND
B21	GND	A21	PERp1
B22	GND	A22	PERn1
B23	PETp2	A23	GND
B24	PETn2	A24	GND
B25	GND	A25	PERp2
B26	GND	A26	PERn2
B27	PETp3	A27	GND
B28	PETn3	A28	GND
B29	GND	A29	PERp3
B30	NC	A30	PERn3
B31	RSVD	A31	GND
B32	GND	A32	NC

PEG1: PCI Express x16



Pin	Signal	Pin	Signal
B1	+ 12V	A1	NC
B2	+ 12V	A2	+ 12V
B3	NC	A3	+ 12V
B4	GND	A4	GND
B5	SMB_CK	A5	TCK
B6	SMB_DAT	A6	TDI
B7	GND	A7	NC
B8	+ 3.3V	A8	TMS
B9	TRST#	A9	+ 3.3V
B10	+3.3VSB	A10	+ 3.3V
B11	WAKE#	A11	PERST#
B12	NC	A12	GND
B13	GND	A13	REFCLK+
B14	PETp0	A14	REFCLK-
B15	PETn0	A15	GND
B16	GND	A16	PERp0
B17	RSVD	A17	PERn0
B18	GND	A18	GND
B19	PETp1	A19	NC
B20	PETn1	A20	GND
B21	GND	A21	PERp1
B22	GND	A22	PERn1
B23	PETp2	A23	GND
B24	PETn2	A24	GND
B25	GND	A25	PERp2
B26	GND	A26	PERn2
B27	PETp3	A27	GND
B28	PETn3	A28	GND
B29	GND	A29	PERp3
B30	NC	A30	PERn3
B31	RSVD	A31	GND
B32	GND	A32	NC
B33	PETp4	A33	NC
B34	PETn4	A34	GND
B35	GND	A35	PERp4
B36	GND	A36	PERn4
B37	PETp5	A37	GND
B38	PETn5	A38	GND
B39	GND	A39	PERp5
B40	GND	A40	PERn5
B41	PETp6	A41	GND

Pin	Signal	Pin	Signal
B42	PETn6	A42	GND
B43	GND	A43	PERp6
B44	GND	A44	PERn6
B45	PETp7	A45	GND
B46	PETn7	A46	GND
B47	GND	A47	PERp7
B48	NC	A48	PERn7
B49	GND	A49	GND
B50	PETp8	A50	NC
B51	PETn8	A51	GND
B52	GND	A52	PERp8
B53	GND	A53	PERn8
B54	PETp9	A54	GND
B55	PETn9	A55	GND
B56	GND	A56	PERp9
B57	GND	A57	PERn9
B58	PETp10	A58	GND
B59	PETn10	A59	GND
B60	GND	A60	PERp10
B61	GND	A61	PERn10
B62	PETp11	A62	GND
B63	PETn11	A63	GND
B64	GND	A64	PERp11
B65	GND	A65	PERn11
B66	PETp12	A66	GND
B67	PETn12	A67	GND
B68	GND	A68	PERp12
B69	GND	A69	PERn12
B70	PETp13	A70	GND
B71	PETn13	A71	GND
B72	GND	A72	PERp13
B73	GND	A73	PERn13
B74	PETp14	A74	GND
B75	PETn14	A75	GND
B76	GND	A76	PERp14
B77	GND	A77	PERn14
B78	PETp15	A78	GND
B79	PETn15	A79	GND
B80	GND	A80	PERp15
B81	NC	A81	PERn15
B82	NC	A82	GND

6.6 Digital Display Interface


DDI1: DDI 1~3/SDVO Signals



Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
B1	+ 12V	A1	HDMIC_CK	B42	DDI2_PR-N2	A42	GND
B2	+ 12V	A2	+ 12V	B43	GND	A43	DDI2_CTRLCLK_AUXP
B3	RSVD	A3	+ 12V	B44	GND	A44	DDI2_CTRLDAT_AUXN
B4	GND	A4	GND	B45	DDI2_PR-P3	A45	GND
B5	SMB_CK	A5	NC	B46	DDI2_PR-N3	A46	GND
B6	SMB_DAT	A6	NC	B47	GND	A47	DDI2_HPD
B7	GND	A7	NC	B48	NC	A48	DDI2_DDC_AUX
B8	+ 3.3V	A8	NC	B49	GND	A49	GND
B9	NC	A9	+ 3.3V	B50	DDI3_PR-P0	A50	NC
B10	+3.3VSB	A10	+ 3.3V	B51	DDI3_PR-N0	A51	GND
B11	WAKE#	A11	PERST#	B52	GND	A52	HDMID_CK
B12	NC	A12	GND	B53	GND	A53	HDMID_DT
B13	GND	A13	NC	B54	DDI3_PR-P1	A54	GND
B14	DDI1_PR-P0 / SDVOB_RED+	A14	NC	B55	DDI3_PR-N1	A55	GND
B15	DDI1_PR-N0 / SDVOB_RED-	A15	GND	B56	GND	A56	NC
B16	GND	A16	DDI1_PR-P5 / SDVO_TVCLKIN+	B57	GND	A57	NC
B17	DDI1_CLK / SDVO_CLK	A17	DDI1_PR-N5 / SDVO_TVCLKIN-	B58	DDI3_PR-P2	A58	GND
B18	GND	A18	GND	B59	DDI3_PR-N2	A59	GND
B19	DDI1_PR-P1 / SDVOB_GRN+	A19	NC	B60	GND	A60	DDI3_CTRLCLK_AUXP
B20	DDI1_PR-N1 / SDVOB_GRN-	A20	GND	B61	GND	A61	DDI3_CTRLCLK_AUXN
B21	GND	A21	DDI1_PR-P4 / SDVOB_INT+	B62	DDI3_PR-P3	A62	GND
B22	GND	A22	DDI1_PR-N4 / SDVOB_INT-	B63	DDI3_PR-N3	A63	GND
B23	DDI1_PR-P2 / SDVOB_BLU+	A23	GND	B64	GND	A64	DDI3_HPD
B24	DDI1_PR-N2 / SDVOB_BLU-	A24	GND	B65	GND	A65	DDI3_DDC_AUX
B25	GND	A25	DDI1_PR-P6 / SDVO_FLDSTALL+	B66	NC	A66	GND
B26	GND	A26	DDI1_PR-N6 / SDVO_FLDSTALL-	B67	NC	A67	GND
B27	DDI1_PR-P3 / SDVOB_CK+	A27	GND	B68	GND	A68	NC
B28	DDI1_PR-N3 / SDVOB_CK-	A28	GND	B69	GND	A69	NC
B29	GND	A29	DDI1_HPD	B70	NC	A70	GND
B30	NC	A30	DDI1_DDC_AUX	B71	NC	A71	GND
B31	DDI1_DAT / SDVO_DAT	A31	GND	B72	GND	A72	NC
B32	GND	A32	NC	B73	GND	A73	NC
B33	DDI2_PR-P0	A33	NC	B74	NC	A74	GND
B34	DDI2_PR-N0	A34	GND	B75	NC	A75	GND
B35	GND	A35	NC	B76	GND	A76	NC
B36	GND	A36	NC	B77	GND	A77	NC
B37	DDI2_PR-P1	A37	GND	B78	NC	A78	GND
B38	DDI2_PR-N1	A38	GND	B79	NC	A79	GND
B39	GND	A39	NC	B80	GND	A80	NC
B40	GND	A40	NC	B81	HDMIC_DT	A81	NC
B41	DDI2_PR-P2	A41	GND	B82	NC	A82	GND

6.7 LPC Debug


CN37: LPC Debug header



Pin	Signal	Pin	Signal
1	LPC_CLK	2	GND
3	LPC_FRAME#	4	KEY
5	LPC_RST#	6	+ 5V
7	LPC_AD3	8	LPC_AD2
9	+ 3.3V	10	L_AD1
11	LPC_AD0	12	GND
13	SMB_CK	14	SMB_DAT
15	SPD_A1 (See JP3)	16	SPD_A0 (See JP4)
17	GND	18	LPC_SERIRQ
19	KBRST#	20	A20GATE#

CN40: LPC Test Connector

(compatible with ADLINK
LPC Debug Card)




Pin	Signal	Pin	Signal
1	LPC_DRQ0#	2	LPC_AD0
3	LPC_DRQ1#	4	LPC_AD1
5	LPC_SERIRQ	6	LPC_AD2
7	LPC_FRAME#	8	LPC_AD3
9	LPC_RST#	10	GND
11	LPC_CLK	12	GND

External LPC EEPROM Address Selection


JP25 & JP26 configure the address of the external EEPROM connected to the LPC Debug header (CN37)

JP6: EEPROM Address A0 Selection



Jumper	Status
1-2	High "1" <<<<
2-3	Low "0"

JP5: EEPROM Address A1 Selection




Jumper	Status
1-2	High "1" <<<<
2-3	Low "0"

Note: <<<< indicates default setting


6.8 I²C and SMB Bus (for user access)

CN33: I²C Bus



Pin	Signal
1	+5V
2	I2C_DAT
3	I2C_CK
4	GND

CN34: SMB Bus



Pin	Signal
1	+5V
2	SMB_DAT
3	SMB_CK
4	GND

I2C/SMBus Buffers

These buffers settings are for isolation of the I2C and SMBus - test feature only.

ON: I2C/SMBus passes through LTC4300A-2 Buffer


OFF: Bypass Buffer

JP19: I²C BUFFER (data)




Jumper	Status
1-2	ON
2-3	OFF <<<<

JP20: I²C BUFFER (clock)




Jumper	Status
1-2	ON
2-3	OFF <<<<

JP21: SMBus BUFFER (data)



Jumper	Status
1-2	ON
2-3	OFF <<<<

JP22: SMBus BUFFER (clock)




Jumper	Status
1-2	ON
2-3	OFF <<<<

Note: <<<< indicates default setting

I²C EEPROM Address Selection


JP29 to JP31 configure the address of the A0, A1 and A2 bits of the I2C EEPROM

JP29: I²C EEPROM A0




Jumper	Status
1-2	A0_HIGH "1"
2-3	A0_LOW "0" <<<<

JP30: I²C EEPROM A1



Jumper	Status
1-2	A1_HIGH "1"
2-3	A1_LOW "0" <<<<

JP31: I²C EEPROM A2




Jumper	Status
1-2	A2_HIGH "1"
2-3	A2_LOW "0" <<<<

Note: <<<< indicates default setting


6.9 USB and LAN

CN15: USB x4 Connector




Pin	Signal
1	+5V
2	USB-
3	USB+
4	Ground

CN45: USB 3.0 x4 Connector



Pin	Signal
1	USB3.0_P5VA
2	USB2_CMAN
3	USB2_CMAP
4	GND
5	USB3A_CMRXN
6	USB3A_CMRXP
7	GND
8	USB3A_CMTXN
9	USB3A_CMTXP


CN18: RJ-45 GbE



Pin	Signal
1	BI_DA+
2	BI_DA-
3	BI_DB+
4	BI_DC+
5	BI_DC-
6	BI_DB-
7	BI_DD+
8	BI_DD-


6.10 Audio

CN25: HD Audio Panel I/O




Pin	Signal	Pin	Signal
1	MIC-In-L	2	AGND
3	MIC-In-R	4	ACZ Detect
5	Line-In-R	6	MIC-In Detect
7	Front I/O Sense	8	Key
9	Line-In-L	10	Line-In Detect

CN26: CD Audio-out Connector



Pin	Signal
1	LINR
2	AGND
3	AGND
4	LINL

CN27: S/PDIF Output Jack (optical)



CN28: S/PDIF Output Header




Pin	Signal	Pin	Signal
1	SPDIF-Out	2	GND

CN29: S/PDIF Input Header




Pin	Signal	Pin	Signal
1	SPDIF-In	2	GND

CN30: Six-in-One Audio Phone Jack



Color	Signal
BLUE	Line-In
GREEN	Line-Out
PINK	MIC-In
ORANGE	Center/Subwoofer
BLACK	Rear Speaker Out
GRAY	Side Speaker Out


CN31: AC'97 Pin Header



Pin	Signal	Pin	Signal
1	GND	2	AC_SYNC
3	AC_SDOUT	4	AC_RST#
5	AC_BITCLK	6	GND
7	AC_SDINO	8	NC


6.11 VGA, LVDS

CN9: LVDS Flat Panel Connector




Pin	Signal	Pin	Signal
1	LVDS_I2C_DAT	2	LVDS_I2C_CK
3	N.C	4	N.C
5	GND	6	LVDS_A0-
7	LVDS_A0+	8	LVDS_VDD_EN
9	LVDS_A1-	10	LVDS_A1+
11	LVDS_BKLT_EN	12	LVDS_A2+
13	LVDS_A2-	14	N.C
15	LVDS_A_CK-	16	LVDS_A_CK+
17	N.C	18	LVDS_A3+
19	LVDS_A3-	20	GND
21	LVDS_B0-	22	LVDS_B0+
23	GND	24	LVDS_B1-
25	LVDS_B1+	26	GND
27	LVDS_B2-	28	LVDS_B2+
29	GND	30	LVDS_B_CK+
31	LVDS_B_CK-	32	N.C
33	LVDS_B3+	34	LVDS_B3-

CN8A: VGA



Pin	Signal	Pin	Signal
1	Red	2	Green
3	Blue	4	NC
5	GND	6	GND
7	GND	8	GND
9	NC	10	GND
11	DDC Power	12	DDC2B Data
13	HSYNC	14	Vsync
15	DDC2B clock		

CN10: Backlight Control



Pin	Signal	Pin	Signal
1	GND	2	Panel PWR
3	Backlight CTRL	4	GND
5	Backlight Enable	6	GND
7	NC	8	Backlight PWR



See 6.12 LVDS Jumper Settings for Panel Power Voltage (JP6), Backlight Power Voltage (JP5) and other LVDS jumper settings.




To avoid damage to the display panel, be sure to set the Panel Power Voltage (JP6) and Backlight Power Voltage (JP5) to the correct values for your display.

6.12 LVDS Jumper Settings

JP5: Backlight Power Voltage


Selects the Backlight Power voltage on CNY8 Backlight Control pin header (pin 8).



Jumper	Status
1-2	+ 12V
2-3	+ 5V <<<<

JP6: Panel Power Voltage


Selects the Panel Power voltage on CNY8 Backlight Control pin header (pin 2).



Jumper	Status
1-2	+ 3.3V <<<<
2-3	+ 5V

JP7: Backlight Enable Signal Type


Sets the *Backlight Enable Signal* to "Normal" or "Inverse" type.



Jumper	Status
1-2	Inverse
2-3	Normal <<<<

JP8: Brightness Control


Sets the Panel Brightness Control (CNY8 pin 3: *Backlight CTRL*) to *Voltage Level* or *PWM*. When set to *Voltage Level*, the *Backlight CTRL* signal can be varied from 0~5V in 0.5V increments.



Jumper	Status
1-2	Voltage Level
2-3	PWM <<<<

JP9: Brightness PWM Source

Sets the Panel Brightness PWM Source to *GPU* or *LVDS I2C*. When Brightness PWM Source is set to *LVDS I2C*, the user will be able to use the AIDI Library *AidiVgaSetBacklight* command to control the PWM pulse to the panel backlight.




Jumper	Status
1-2	GPU
2-3	LVDS I2C <<<<

Note: <<<< indicates default setting


6.13 Keyboard & Mouse

CN19: *Mouse (top)*



Pin	Signal
1	MSDAT
2	NC
3	GND
4	KB5V
5	MSCLK
6	NC

Keyboard (bottom)



Pin	Signal
1	KBDAT
2	NC
3	GND
4	KB5V
5	KBCLK
6	NC

6.14 Storage: SATA

CN11/12/13/14: *SATA*




Pin	Signal	Pin	Signal
1	GND	2	Tx+
3	Tx-	4	GND
5	Rx-	6	Rx+
7	GND		

6.15 Serial and IrDA Ports


Serial Ports from Super I/O

CN8B: COM1 (DB9)



Pin	Signal	Pin	Signal
6	DSR	1	DCD#
7	RTS#	2	RXD
8	CTS#	3	TXD
9	RI#	4	DTR#
		5	GND

CN21: COM2 (header)



Pin	Signal	Pin	Signal
1	DCD#	2	DSR
3	RXD	4	RTS#
5	TXD	6	CTS#
7	DTR#	8	RI#
9	GND	10	NC


CN22: IrDA Connector



Pin	Signal
1	+5V
2	No connect
3	IrRXD
4	Ground
5	IrTXD


Serial Ports from Module

CN6: COMO (header)



Pin	Signal	Pin	Signal
1	NC	2	NC
3	SER0_RX	4	NC
5	SER0_TX	6	NC
7	NC	8	NC
9	GND	10	NC

CN7: COM1 (header)




Pin	Signal	Pin	Signal
1	NC	2	NC
3	SER1_RX	4	NC
5	SER1_TX	6	NC
7	NC	8	NC
9	GND	10	NC



CN6 and CN7 are the General Purpose Serial Interface ports from the module, new for COM.0 Rev. 2.


6.16 Fan Connectors

JP35, JP36, JP37:



Jumper	Status
1-2	4-pin
2-3	3-pin

FAN1-3: 12V Fan Power



Pin	Signal
1	GND
2	Fan Power 12 V
3	Fan Speed Sense
4	Fan Speed Control (PWM)

FAN4: 5V Fan Power



Pin	Signal
1	Fan Power 5V
2	GND
3	Fan Speed Sense




NOTE: FAN3 PWM is controlled by the module (B101: FAN_PWMOUT, B102: FAN_TACHIN). The "sense" and "speed" signals of FAN1/2/4 are connected to the Super IO.

6.17 Power Connectors


CN1: ATX 24-pin Power Connector

Connect the ATX 24-pin (or 20-pin) connector to supply power to the Express-BASE6 carrier.



CN5: ATX 12V 4-pin Connector

Connect the ATX 12V 4-pin connector to supply power to the COM Express module.



Pin	Signal
1	GND
2	GND
3	+12V
4	+12V




All 12V power for the COM Express module is provided by the ATX 12V 4-pin connector. The system will not power up if CN42 is not connected to the power supply.



To avoid damage to the carrier board and installed components, be sure to connect the ATX power supply to the correctly connectors. See *8.5 ATX Power Connectors* on page 37 for detailed information.

CN44: Smart Battery


Connects to Smart Battery module



Pin	Signal	Pin	Signal
1	I2C_CK	6	SUS_S45#
2	I2C_DAT	7	+12V
3	PWRBTN#	8	+5VSB
4	BATLOW#	9	SUS_STAT#
5	PS_ON#	10	GND

6.18 Power Jumper Settings


CN2: PWR_OK Config



Jumper	Status
1-2	Add 3.3V Pullup with 10K to signal PWR_OK
3-4	Connect PWRGOOD of ATX power supply <<<<
5-6	Connect PWRGOOD of onboard DCDC regulator

JP1: AT/ATX MODE

In AT mode, JPY1 shorts PS_ON# to ground directly to force power on. See *8.6 AT Power Mode* on p. 38.




Jumper	Status
1-2	ATX Mode <<<<
2-3	AT Mode

JP2: PS_ON# Signal Source

All ADLINK modules support S3 mode and consecutive power down of ATX power supply. For modules that connect the S3 signal, PS_ON#


should always be set to SUS_S3# as source (even when S3 mode is disabled in the BIOS). For modules that do not bring out the S3 signal, PS_ON# should be set to SUS_S5# as source.



Jumper	Status
1-2	SUS_S3# <<<<
2-3	SUS_S5#


JP3: AT Power 5V Setting

With an AT power supply is connected to the Express-BASE6, JP3 can be used to provide 5VSB to the COM module from the carrier board.



Jumper	Status
1-2	AT without P5V <<<<
2-3	AT with P5V

JP3: 5VSB to Module Source



Jumper	Status
1-2	5VSB produced on carrier from Vcc
2-3	5VSB from ATX power supply
3-4	No 5VSB from module

Note: <<<< indicates default setting

6.19 Other Connectors


CN36/CN39: GPIO Headers

GPIOs of CN36 come from the COM Express module. GPIOs of CN39 come from Express-BASE6.



Pin	Signal	Pin	Signal
1	GPIO	2	GPO0
3	GPI1	4	GPO1
5	GPI2	6	GPO2
7	GPI3	8	GPO3


CN32: Miscellaneous Connector



Pin	Signal	Pin	Signal
1	Power_LED	11	BUZZER
2	WDT_LED	12	NC
3	GND	13	NC
4	NC	14	+5V
5	GND	15	SYS_RESET
6	GND	16	GND
7	NC	17	ATA_ACT
8	PS_ON	18	+3.3V
9	5V STB	19	PWR_BTN
10	SIO_PME	20	GND


CN41/42: Digital I/O

The Express-BASE6 provides GPIO expansion for I²C applications via a Phillips PCA955 with 16-bit I²C I/O port and interrupt (for CN41 n=0, for CN42 n=1). See 8.4 *Digital I/O LEDs* on p. 36 for CN41 LED descriptions.



Pin	Signal	Pin	Signal
1	I/O n.0	11	GND
2	I/O n.1	12	GND
3	I/O n.2	13	GND
4	I/O n.3	14	GND
5	I/O n.4	15	GND
6	I/O n.5	16	GND
7	I/O n.6	17	GND
8	I/O n.7	18	GND
9	INT#	19	BATLOW#
10	3V3	20	+3.3V


CN43: Feature Connector



Pin	Signal	Pin	Signal
1	+5V	2	+5VSB
3	+5V	4	Hard Disk Activity
5	I2C_DAT	6	SMBCLK_SB
7	I2C_CK	8	SMBDATA_SB
9	Internal use	10	GPO0
11	Internal use	12	GPO1
13	PS_ON#	14	GPO2
15	SUS_S3#	16	GPO3
17	GND	18	GND
19	THRMTRIP#	20	SMBALRT#
21	GPI1	22	SUS_S4#
23	SUS_STAT#	24	GPI0
25	GPI2	26	SUS_S5#
27	WDTRIG	28	THRM#
29	GPI3	30	PCI_M66EN
31	BATLOW#	32	WAKE1#
33	PEG_ENABLE#	34	PEG_LANE_RV#
35	KBINH#	36	SYS_RESET#
37	GND	38	GND
39	PWBTN#	40	PWR_OK

U55: Secondary SPI BIOS Socket

See JP23/JP24 BIOS Selection Jumpers on page 32 and 7.1 SPI Secondary BIOS on page 34 for detailed information.



Pin	Signal
1	CS#
2	DO
3	WP#
4	GND
5	DI
6	CLK
7	HOLD#
8	+3.3V

6.20 Other Jumper Settings

JP4: Clear CMOS

To clear CMOS, shut down the power and short pins 2 and 3 (shorts VBAT to ground).



Jumper	Status
1-2	Normal <<<<
2-3	Clear CMOS

JP17: RSVD

JP18: Super I/O

Enables/disables the Super IO. By default, the Express-BASE6 enables the onboard W83627DHG-PT Super I/O. To disable the Onboard Super I/O, short pins 2-3 of Jumper JP18.



Jumper	Status
1-2	Enable <<<<
2-3	Disable

JP23/24: BIOS Selection


See 7.1 SPI Secondary BIOS on page 34 for a detailed description.



JP23	JP24	Status
1-2	1-2	Module BIOS <<<<
2-3	1-2	Reserved
1-2	2-3	Carrier SPI BIOS
2-3	2-3	Reserved

JP32: TPM Signal Jumper

Configuring the jumper to "ON" pulls the TPM signal high and "OFF" does nothing to the TPM signal. Dependent upon module's design for the TPM signal.



Jumper	Status
1-2	ON
2-3	OFF <<<<

Note: <<<< indicates default setting


7 Secondary BIOS

The Express-BASE6 supports Secondary BIOS using Serial Peripheral Interface (SPI) for COM.0 Rev. 2.0 modules. Secondary BIOS solutions can be used as an alternative to the on-module BIOS and provide support for the following:

- ▶ Testing new BIOS versions
- ▶ Development of firmware modifications
- ▶ Recovery if soldered BIOS on module is corrupted


7.1 SPI Secondary BIOS

SPI is supported by PICMG COM.0 Rev. 2.0 to provide a Secondary BIOS for COM Express Rev 2.0 modules that support a SPI Secondary BIOS.




To use the BIOS on the module:

- ▶ Short pins 1-2 on both JP23 and JP24.



To use the SPI BIOS on the carrier board:


- ▶ Short pins 1-2 on JP23, pins 2-3 on JP24.



Open the SPI BIOS socket and insert the secondary BIOS flash chip.


8 Switches, POST, LEDs & Power

8.1 Mini Switches (SW1~4)



There are two mini switches at the top left corner of the board.


The **SW1** switch is the **ATX Power Button**.
The **SW2** switch is the **Reset Button**.



At the top edge of the board are two more switches.

The **SW3** switch is the **Sleep Button** and the **SW4** switch is the **Lid Button**. Both buttons support Type 6 modules for ACPI power management behavior settings in an OS environment.


8.2 Module Type Display



To the left of the Express Card socket , 6 mini LEDs (LED6 ~11) indicate the **type of COM Express** module installed on the Express-BASE6.

COM Express type: 1-2, 3, 4, 5, 6 or wrong pinout


8.3 POST & Indicator LEDs




An LPC based POST display is added for debugging. The two LEDs shows the actual **POST data**.

A row of mini LEDs to the left of the POST display indicates the following:

- LED1** 5Vsb: ATX power attached on standby or active
- LED3** PWR: Indicates power on
- LED20** HDD: Indicates hard drive activity
- LED23** S3: Indicates S3 status




8.4 Digital I/O LEDs



LED12 - LED19 are indicators for the Digital I/O connector CN41. When the I/O signal is high, the LED will light. The **I/O 0** signal corresponds to LED19, and the **I/O 7** signal corresponds to LED12.

8.5 ATX Power Connectors




The Express-BASE6 has one **ATX 24-pin connector** to supply power to the carrier board and one **ATX 12V 4-pin connector** to supply power to the COM Express module.




The system will not power on unless an ATX 12V 4-pin connector is connected.

If your power supply has a **24-pin ATX connector**, then attach the connectors as shown.




If your power supply has a **20-pin ATX connector**, then attach the connectors as shown.



DO NOT plug the ATX 12V 4-pin connector into the ATX 24-pin power connector.

8.6 AT Power Mode

To operate the system in AT Mode with an ATX power supply, use the AT mode PSU converter cable (no 5Vsb) to connect the ATX 20/24-pin power connector to the carrier board as shown.



Set the ATX/AT Mode jumper JP1 to *AT Mode* as described in *6.17 Power Jumper Settings*.

Important Safety Instructions

For user safety, please read and follow all instructions, **warnings**, **cautions**, and **notes** marked in this manual and on the associated equipment before handling/operating the equipment.

- ▶ Read these safety instructions carefully.
- ▶ Keep this user's manual for future reference.
- ▶ Read the specifications section of this manual for detailed information on the operating environment of this equipment.
- ▶ When installing/mounting or uninstalling/removing equipment:
 - Turn off power and unplug any power cords/cables.
- ▶ To avoid electrical shock and/or damage to equipment:
 - Keep equipment away from water or liquid sources;
 - Keep equipment away from high heat or high humidity;
 - Keep equipment properly ventilated (do not block or cover ventilation openings);
 - Make sure to use recommended voltage and power source settings;
 - Always install and operate equipment near an easily accessible electrical socket-outlet;
 - Secure the power cord (do not place any object on/over the power cord);
 - Only install/attach and operate equipment on stable surfaces and/or recommended mountings; and,
 - If the equipment will not be used for long periods of time, turn off and unplug the equipment from its power source.
- ▶ Never attempt to fix the equipment. Equipment should only be serviced by qualified personnel.
- ▶ A Lithium-type battery may be provided for uninterrupted, backup or emergency power.



Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.

- ▶ Equipment must be serviced by authorized technicians when:
 - The power cord or plug is damaged;
 - Liquid has penetrated the equipment;
 - It has been exposed to high humidity/moisture;
 - It is not functioning or does not function according to the user's manual;
 - It has been dropped and/or damaged; and/or,
 - It has an obvious sign of breakage.

Getting Service

Contact us should you require any service or assistance.

ADLINK Technology, Inc.

Address: 9F, No.166 Jian Yi Road, Zhonghe District
New Taipei City 235, Taiwan
新北市中和區建一路 166 號 9 樓
Tel: +886-2-8226-5877
Fax: +886-2-8226-5717
Email: service@adlinktech.com

Ampro ADLINK Technology, Inc.

Address: 5215 Hellyer Avenue, #110, San Jose, CA 95138, USA
Tel: +1-408-360-0200
Toll Free: +1-800-966-5200 (USA only)
Fax: +1-408-360-0222
Email: info@adlinktech.com

ADLINK Technology (China) Co., Ltd.

Address: 上海市浦东新区张江高科技园区芳春路 300 号 (201203)
300 Fang Chun Rd., Zhangjiang Hi-Tech Park,
Pudong New Area, Shanghai, 201203 China
Tel: +86-21-5132-8988
Fax: +86-21-5132-3588
Email: market@adlinktech.com

ADLINK Technology Beijing

Address: 北京市海淀区上地东路 1 号盈创动力大厦 E 座 801 室(100085)
Rm. 801, Power Creative E, No. 1,
Shang Di East Rd., Beijing, 100085 China
Tel: +86-10-5885-8666
Fax: +86-10-5885-8626
Email: market@adlinktech.com

ADLINK Technology Shenzhen

Address: 深圳市南山区科技园南区高新南七道 数字技术园
A1 栋 2 楼 C 区 (518057)
2F, C Block, Bldg. A1, Cyber-Tech Zone, Gao Xin Ave. Sec. 7,
High-Tech Industrial Park S., Shenzhen, 518054 China
Tel: +86-755-2643-4858
Fax: +86-755-2664-6353
Email: market@adlinktech.com

LIPPERT ADLINK Technology GmbH

Address: Hans-Thoma-Strasse 11, D-68163, Mannheim, Germany
Tel: +49-621-43214-0
Fax: +49-621 43214-30
Email: emea@adlinktech.com

ADLINK Technology, Inc. (French Liaison Office)

Address: 15 rue Emile Baudot, 91300 Massy CEDEX, France
Tel: +33 (0) 1 60 12 35 66
Fax: +33 (0) 1 60 12 35 66
Email: france@adlinktech.com

ADLINK Technology Japan Corporation

Address: 〒101-0045 東京都千代田区神田鍛冶町 3-7-4
神田 374 ビル 4F
KANDA374 Bldg. 4F, 3-7-4 Kanda Kajicho,
Chiyoda-ku, Tokyo 101-0045, Japan
Tel: +81-3-4455-3722
Fax: +81-3-5209-6013
Email: japan@adlinktech.com

ADLINK Technology, Inc. (Korean Liaison Office)

Address: 서울시 서초구 서초동 1675-12 모인터빌딩 8 층
8F Mointer B/D,1675-12, Seocho-Dong, Seocho-Gu,
Seoul 137-070, Korea
Tel: +82-2-2057-0565
Fax: +82-2-2057-0563
Email: korea@adlinktech.com

ADLINK Technology Singapore Pte. Ltd.

Address: 84 Genting Lane #07-02A, Cityneon Design Centre,
Singapore 349584
Tel: +65-6844-2261
Fax: +65-6844-2263
Email: singapore@adlinktech.com

ADLINK Technology Singapore Pte. Ltd. (Indian Liaison Office)

Address: 1st Floor, #50-56 (Between 16th/17th Cross) Margosa Plaza,
Margosa Main Road, Malleswaram, Bangalore-560055, India
Tel: +91-80-65605817, +91-80-42246107
Fax: +91-80-23464606
Email: india@adlinktech.com

ADLINK Technology, Inc. (Israeli Liaison Office)

Address: 6 Hasadna St., Kfar Saba 44424, Israel
Tel: +972-9-7446541
Fax: +972-9-7446542
Email: israel@adlinktech.com



ADLINK
TECHNOLOGY INC.